

# OZOGEN

Providing O<sup>3</sup> Ozone Equipment and Complete Solutions



## OzoPure Multi-Purpose

### Instruction Leaflet

Thanks for your selection of our ozone generator. Please read this leaflet carefully before using and keep it for future reference.

#### Some Applications:

- To drink ozonated water for health purposes, 10 minutes to generate high ozone level in 300ml of cold water bubbling ozone in glass using white stone diffuser provided. Water should be consumed immediately as ozone dissipates quickly. Water should be consumed on an empty stomach to ensure maximum absorption by the body. (20 minutes for 600ml etc) This water can also be used to disinfect cuts, for gargling to remove throat bacteria etc.
- For sanitizing of vegetables or fruit, place vegetables or fruit in basin and bubble using black stone diffuser provided for 20 minutes to resolve artificial chemicals, bacteria etc. Same process can be used for sterilizing baby bottles etc. Water should be as cold as possible as hot water destroys ozone.
- For room sanitation, place unit in room with no connections on ozone outlet and run for 20 minutes for room of 10 square meters. (60 minutes on for 30 square meters etc.)
- For a room sanitation where people are smoking or busy kitchen etc, place unit in room with no connections on ozone outlet and run for 20 minutes on, 20 minutes off cycle for room of 10 square meters. (60 minutes on, 20 minutes off for 30 square meters etc.)

#### Configuration for Water or Air:

For water use, push the supplied silicon pipe over the ozone outlet and fit either the black or white stone diffuser to the other end. White for water consumption, black for fish tanks and vegetables etc.

For air use, use as is with no silicon pipe fitted.

#### Operation:

- Connect the power lead to a 220-240v 50-60Hz power socket. On/Off indicator will turn green to show availability of power.

- Press the "On Time" button to select the duration of time that the unit will generate ozone for. Multiple presses are used to move through the options. Maximum time is 120 minutes.
- Press the "Off Time" button to select the duration of time that the unit will not generate ozone before it switches on again and runs as per the time selected by the "On Time" button.
- Once you have selected the above options, push the On/Off switch to start the unit. The unit will work and pause in cycles as selected by the "On Time" and "Off Time"
- When you are finished using the unit, pull the electricity cord out from the electricity socket and store the unit in a dry place.

#### Indicator Lights:

- When the left light is on, the ozone generator is working.
- When the right light is on, the pump is working.

Both lights should be on together to generate ozone and distribute the ozone. During cooling cycles, only the pump light will be on.

In case of Malfunction, remove the power lead from the electricity socket, wait 10 seconds and then re-insert the power lead.

#### Warning:

To prevent electrical shock, do not submerge the unit in water.

#### Specifications:

- \* Power: 220-240v, 15w
- \* Ozone Rate: 300 to 500 mg/h pending oxygen density of air and humidity
- \* Working Times: 10, 20, 30, 60, 120 minutes
- \* Pausing Times: 20, 30, 60, 120, 180 minutes

\* **IMPORTANT NOTE:** "Working Time" should never be set higher than "Pausing Time" as the unit needs time to cool between cycles/ use.